

INTRODUCTION


Thank you, and congratulations on your choice of the Amazing Machines Volcano - MIDI Output Interface for the KORG Volca Series.

Please note that any modification to any KORG Volca will immediately void its warranty.

Amazing Machines will not accept responsibility for any damages, personal loss or injury that may result from the installation of the Volcano Interface.

Volca is a trademark of KORG Inc. Japan, all other trademarks and copyrights are property of their respective owners.

The following pages of this document provide a step by step installation guide for the Volcano Interface, as well as detailed functionality information.



CONTENTS

Chapter 1 - Volcano Quick Installation Guide - Volca Beats	1
Volcano Quick Installation - Volca Beats - Step 1	2
Volcano Quick Installation - Volca Beats - Step 2	3
Volcano Quick Installation - Volca Beats - Step 3	4
Volcano Quick Installation - Volca Beats - Step 4	5
Volcano Quick Installation - Volca Beats - Step 5	6
Volcano Quick Installation - Volca Beats - Step 6	7
Volcano Quick Installation - Volca Beats - Step 7	8
Volcano Quick Installation - Volca Beats - Step 8	9
Volcano Quick Installation Done - Volca Beats	10
Chapter 2 - Volcano MIDI Output Functionality - Volca Beats	11
Control Change Output	12

CHAPTER 1 - VOLCANO QUICK INSTALLATION GUIDE - VOLCA BEATS

WARNING: Any modification to any KORG Volca will immediately void its warranty.

If you are not sure what you are doing, please ask a technician to do it for you.

Amazing Machines will not accept responsibility for any damages, personal loss or injury that may result from the installation of the Volcano Interface.


We strongly advise you to read every single page of this chapter before proceeding.

For instructions on how to perform a permanent installation of the Volcano Interface by drilling holes for the MIDI Output connector in the case of your KORG Volca, please refer to the "Volcano Permanent Installation Guide", available at www.amazingmachines.com.br

Bill of Tools


- Medium size Phillips screwdriver
 - 60W Soldering iron
 - Solder wire
- Medium size flat tip screwdriver
 - Flat long nose pliers

VOLCANO QUICK INSTALLATION - VOLCA BEATS - STEP 1



1.1 - Using a Phillips Screwdriver, remove the screws from the case

VOLCANO QUICK INSTALLATION - VOLCA BEATS - STEP 2




LOCATE THE SOLDER PADS ON THE KLM-3199 PCB

2.1 - Locate the 3 solder pads on the KLM-3199 PCB


2.2 - Add a touch of solder to the pads, **be careful not to overheat the circuit board as it may cause irreparable damage to your KORG Volca, do it as fast and precisely as you can**

VOLCANO QUICK INSTALLATION - VOLCA BEATS - STEP 3




- 3.1 - Solder the wires to the pads following the labels on the Volcano PCB, **be careful not to overheat the circuit board as it may cause irreparable damage to your KORG Volca**, do it as fast and precisely as you can
- 3.2 - Disconnect the MIDI Output cable from the Volcano PCB

VOLCANO QUICK INSTALLATION - VOLCA BEATS - STEP 4




- 4.1 - Using a Phillips Screwdriver, remove the Custom Built Spacer from the MIDI Output Connector
- 4.2 - Bent the MIDI Output cable to an "L" shape
- 4.3 - Using a Flat Tip Screwdriver, squeeze the spring on the left side of the battery compartment to pass the MIDI Output cable through the hole

VOLCANO QUICK INSTALLATION - VOLCA BEATS - STEP 5



5.1 - Pass the MIDI Output cable through the battery compartment hole


VOLCANO QUICK INSTALLATION - VOLCA BEATS - STEP 6



6.1 - Remove the double-faced tape cover from the Volcano PCB

6.2 - Locate the best spot to attach the Volcano PCB to the KLM-3199 PCB

VOLCANO QUICK INSTALLATION - VOLCA BEATS - STEP 7



ATTACH THE VOLCANO PCB TO THE KLM-3199 PCB

7.1 - Attach the Volcano PCB to the KLM-3199 PCB

7.2 - Using a Flat Long Nose Pliers, gently connect the MIDI Output cable to the CN1 Connector on the Volcano PCB, **make sure the contacts are properly aligned before using the pliers, don't apply too much strenght to the connectors, in order to avoid smashing the plastic parts**

VOLCANO QUICK INSTALLATION DONE - VOLCA BEATS



Congratulations, your Volcano Kit is installed and ready to use.

For instructions on how to perform a permanent installation of the Volcano Interface by drilling holes for the MIDI Output connector in the case of your KORG Volca, please refer to the "Volcano Permanent Installation Guide", available at www.amazingmachines.com.br

Sequencer Output

Start / Stop
MIDI Clock
Note On (Vel 127)
Note Off (Vel 0)

Output Notes - C1, D1, G1, D2, F#1, A#1, D#1, D#4, G3, C#2

- Motion Recorded Data doesn't appear at the MIDI Output Port
 - Stutter Retrigger doesn't appear at the MIDI Output Port
- Muting sequencer parts doesn't mute them at the MIDI Output Port
- The MIDI Output Channel follows the selected MIDI Input Channel

Part Trigger Buttons Output Notes

KICK - C1
SNARE - D1
LO TOM - G1
HI TOM - D2
CL HAT - F#1
OP HAT - A#1
CLAP - D#1
CLAVES - D#4
AGOGO - G3
CRASH - C#2

VOLCANO MIDI OUTPUT FUNCTIONALITY - VOLCA BEATS

Control Change Output

KICK PART LEVEL - 40
SNARE PART LEVEL - 41
LO TOM PART LEVEL - 42
HI TOM PART LEVEL - 43
CL HAT PART LEVEL - 44
OP HAT PART LEVEL - 45
CLAP PART LEVEL - 46
CLAVES PART LEVEL - 47
AGOGO PART LEVEL - 48
CRASH PART LEVEL - 49
CLAP PCM SPEED - 50
CLAVES PCM SPEED - 51
AGOGO PCM SPEED - 52
CRASH PCM SPEED - 53
STUTTER TIME - 54
STUTTER DEPTH - 55
TOM DECAY - 56
HAT CLOSED DECAY - 57
HAT OPEN DECAY - 58
HAT GRAIN - 59

